

LED CEILING SHADE INSTALLATION INSTRUCTIONS

STANDARD[®]

IMPORTANT - READ ALL INSTRUCTIONS BEFORE INSTALLATION

- Installation and maintenance must be performed by licensed electricians only.
- To avoid risk of electric shock, make sure to turn off main power switch prior to installation or maintenance.
- Must be installed in compliance with National Electrical Code (NEC) in the US or Canadian Electrical Code in Canada.
- Ensure input voltage and frequency are compatible with the fixture. Check product manual for power requirements prior to installation.

WARNING: Risk of electric shock. Suitable for damp locations.

- Must be grounded
- Minimum 90 °C supply conductors
- This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved

ELECTRICAL COMPONENTS AND CHARACTERISTICS OF THE LUMINAIRE

- Integral, high efficiency driver and power supply
- Universal AC input voltage (120 V)
- Nominal power factor: 0.95
- Dimming: Yes (refer to the luminaire technical information bulletin for compatible dimmers)

INSTALLATION

1. Drive the screws into the Junction Box, with 2/3 inside and 1/3 outside. (see figure 1)
2. Remove diffuser by twisting out of plate. (see figure 2)
3. Put the Shade cover vertical on the fixture pan. (see figure 3)
4. Connect the black and white and the grounding wire of the luminaires with three wires of the same colour from the junction box with wire caps. (see figure 4, step 1)
5. Tuck all the wires and connections into the Junction Box. Align the Mounting Hole on the fixture to the driven screws and put in, then twist the fixture clockwise. Use the screw driver to adjust the screws outside length and fix the fixture on the ceiling. (see figure 4, step 2)
6. Put the plastic diffuser back onto the luminaire plate and twist into place. (see figure 4, step 3)
7. Turn on power and turn on the light switch to activate the luminaire. (see figure 5)

**Refer to the Ceiling Luminaire installation guide for additional information.*



