



LED 4-Pin PL Electronic Ballast Compatibility Chart

Key:	F	Flicker after >2s start-up,	P	PF <0.85
	N	Acoustic noise >20dB	S	Can't start-up
	T	THD >30%	C	compatible
	O	Can work but LED current over sepc.(300mA)		

Ballast Brand*	Part Number	Start Method	# of Lamp	BF		Lamp Connection	Electrical Characteristic				1-Lamp						2-Lamp					
				Type	Value		Vin (V)	Target Lamp Type	PF	108Vac	120Vac	132Vac	250Vac	277Vac	305Vac	108Vac	120Vac	132Vac	250Vac	277Vac	305Vac	
Robertson	PSM2GPH18MVDW	PS	2			Series	120-277	18W*2		H	O	O			O	O,P	O	O			O	O
SUNPARK	U-226PS-W	PS	2			Series	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			C	P	C	C			C	C
SUNPARK	SL27T	PS	2			Series	120	18W*2 ; 13W*2		N	P,T	P,T	P,T									
SUNPARK	U-213PS	PS	2			Series	120-277	13W*2 ; 13W*1		H	C	C			C	F,P	C	C			P	F
SUNPARK	LC 12010T	PS	1			n/a	120	13W*1		N	P,T	P,T	P,T									
SUNPARK	U-218PS-W	PS	2			Series	120-277	18W*2 ; 18W*1		H	C	C			C	P	C	C			C	C
Philips-Advance	ICF-2S18-H1-LD	PS	2	N	0.95	Series	120-277	18W*2		H	C	C			C	P,T	C	C			C	C
OSRAM SYLVANIA	QTP 2×26/32/42CFUNV DM PEM	PS	2	N	1.00	Series	120-277	26W*2 ; 32W*2 ; 42W*2		H	P,T	P,T			P,T	P,T	F	F			F	F
Universal Lighting Technologies	C218UNVME	PS	2	N	0.95	Series	120-277	18W*2 ; 18W*1		H	C	C			P,T	P	C	C			C	C
HATCH	HC226PS/UV/D	PS	2	N	1.00	Series	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P	P	C	C			C	C
ESPEN	VE126120MR	PS	1	N	0.92	n/a	120	26W*1		N	P,T	P,T	P,T									
ESPEN	VE118120MR	PS	1	N	0.88	n/a	120	18W*1		N	P,T	P,T	O,P,T									
Philips-Advance	VEZ-1T42-M2-LD	DPS	1	N	1.00	n/a	277	26W*1 ; 32W*1 ; 42W*1		H				C	C	C						
HOWARD INDUSTRIES	EP2/42CF/MV/2	PS	2	N	1.00	Series	120-277	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1		H	C	C			P	P	C	C			P	P
Philips-Advance	VEZ-2Q26-M2-LD	DPS	2	N	1.00	Series	277	26W*2		H									C		C	C
Fulham	RHA-UNV-218-C	PS	2	N	1.05	Series	120-277	18W*2 ; 18W*1		H	C	C			P	P	C	C			C	C
Fulham	RHA-UNV-226-C	PS	2	N	1.01	Series	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P	P	C	C			C	C
Philips-Advance	ICF-2S13-H1-LD	PS	2	N	1.00	Series	120-277	13W*2 ; 13W*1		H	C	C			C	P,T	C	C			C	C
Philips-Advance	ICF-2S13-M1-BS	PS	2	N	1.00	Series	120-277	13W*2 ; 13W*1		H	C	C			C	P,T	C	C			C	C
Philips-Advance	RCF-2S13-M1-BS-QS	RS	2	N	1.00	Series	120	13W*2 ; 13W*1		H	C	C	C				C	C	C			
ProLume	EP2CF13PS/MV/DC/K	PS	2	N	1.00	Series	120-277	13W*2 ; 13W*1 ; 18W*1		H	C	C			C	P	C	C			C	P
ProLume	EP2CF18PS/MV/DC/K	PS	2	N	0.95	Series	120-277	18W*2 ; 18W*1 ; 26W*1		H	C	C			C	C	C	C			C	C
ProLume	EP2CF26PS/MV/DC/K	PS	2	N	1.00	Series	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P	P	C	C			C	C
ProLume	EP2CF42PS/MV/DC/K	PS	2	N		Series	120-277	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1		H	C	C			P	P	C	C			P	P
Philips-Advance	HDF226T4(IPW2S26M5LS)	DPS	2	N	0.03~1.00	Series	120-277	13W*2 ; 13W*1 ; 18W*2 ; 18W*1 ; 26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			C	C	C	C			C	C
Deltek Ballast	80208 CFL226MVRSL	RS	2			Series	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	O	O			O	O,P	O	O			O	O
Fulham (PONY)	NPY-120-126CFL	RS	1	N	1.00	n/a	120	26W*1 ; 32W*1		N	O,P,T	O,P,T	O,P,T									
Fulham(WORKHORSE)	WH3-120-C	IS	2	N	1.01	Parallel	120	26W*1 ; 32W*1		H	T	T	T				T	T	T			
GE	GEC218-MVPS-3W	PS	2	N	1.05	Series	120-277	18W*2 ; 18W*1 ; 26W*1		H	C	C			P,T	P,T	C	C			P	P
GE	GEC226-MVPS-3W	PS	2	N	1.02	Series	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P	P,T	C	C			C	C
DAMAR	23350D	PS	2			Series	120-277	13W*2 ; 13W*1 ; 18W*2 ; 18W*1		H	C	C			C	T	C	C			C	C
Philips-Advance	ICF-2S42-M2-LD	PS			Series	2	120-277	26W*2 ; 32W*2 ; 42W*2		H	C	C			P	P	C	C			P	P
Philips-Advance	ICF-2S26-H1-LD	PS			Series	2	120-277	26W*2 ; 26W*1		H												
Philips-Advance	VEZ-1T42-M2-BS	DPS			n,a	1	277	26W*1 ; 32W*1 ; 42W*1		H				C	C	C						
Universal Lighting Technologies	C2642UNVME	PS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			C	C	C	C			C	C
HATCH	HC242PS/UV/D	PS			Series	2	120-277	26W*2 ; 32W*2 ; 42W*2		H	C	C			P	P	C	C			P	P
AC ELECTRONICS	CSS-UV42PS	PS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P,T	P,T	C	C			C	C
AC ELECTRONICS	CSD-UV42PS	PS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1		H	C	C			P,T	P,T	C	C			C	C
General Electric	GEC242-MVPS-3W	PS			Series	2	120-277	26W*2 ; 32W*2 ; 42W*2 ; 42W*1		H	C	C			P,T	P,T	C	C			P,T	P,T
Philips-Advance	ICF-2S26-M1-BS	PS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P,T	P,T	C	C			C	C
KEYSTONE	KTEB-242-UV-RS-DW	RS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1		H	O	O			O	O	S	S			S	S
KEYSTONE	KTEB-242-UV-PS-DW	PS		N	Series	2	120-277	26W*2 ; 26W*1 ; 32W*2 ; 32W*1 ; 42W*2 ; 42W*1		H	C	C			P	P	C	C			P	P
KEYSTONE	KTEB-226-UV-RS-DW	RS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			C	C	O	O			O	O
KEYSTONE	KTEB-226-UV-PS-DW	PS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P	P	C	C			C	C
KEYSTONE	KTEB-218-UV-RS-DW	RS			Series	2	120-277	18W*2 ; 18W*1 ; 26W*1		H	C	C			C	P	C	C			C	C
KEYSTONE	KTEB-218-UV-PS-DW	PS			Series	2	120-277	18W*2 ; 18W*1 ; 26W*1		H	C	C			P	P	C	C			C	P
Universal Lighting Technologies	C213UNVME	PS			Series	2	120-277	13W*2 ; 13W*1		H	C	C			C	P	C	C			C	C
OSRAM SYLVANIA	QTP 2×26CF/UNV DM	PS			Series	2	120-277	26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	C	C			P	P	C	C			C	C
OSRAM SYLVANIA	QTP 2×26/32/42CFUNV DM	PS			Series	2	120-277	26W*2 ; 32W*2 ; 42W*2		H	F	F			F	P,T	P,T	P,T			P,T	P,T
TOPAZ	B2642UNV/ME-TPZ	PS			Series	2	120-277	18W*2 ; 26W*2 ; 26W*1 ; 32W*1 ; 42W*1		H	F	F			F,P,T	F	C	C			C	P,T

Applies to the following **Satco** products: S9850, S9851, S9852, S9853; S9858, S9859, S9860, S9861

* All trademarks are the property of their respective owners

Copyright© 2016	Distribution Centers:	National Toll-Free:	110 Heartland Blvd.
Satco Products, Inc.	New York, Florida,	800-43-SATCO	Brentwood, NY 11717
All Rights Reserved.	Texas, Washington,	(800-437-2826)	PH 631-243-2022
Rev: October 21, 2016	California, Pureto Rico	www.satco.com	FX 631-243-2027